



VHF FM TRANSCEIVERS

IC-V80
(U.S.A. Version)

IC-V80E
(Europe Version)

Rugged and Basic 2M with Powerful Audio!

Icom radios are built tough, and the IC-V80/E – Icom's most economical 2M – is no exception. This military rugged rig offers water resistance and superior protection against dust and dirt (IP54). Compact, rugged and with plenty of power, the IC-V80/E is ideal for basic, on-the-go ham operations.

750mW loud audio

The IC-V80/E uses the BTL (bridge-tied load) amplifier that doubles the audio output. The 36mm large speaker delivers 750mW of loud and intelligible audio*. Great for noisy environments.

* Typical value using with internal speaker.

Built-in CTCSS/DTCS

The CTCSS and DTCS tone codes provide quiet stand-by and allow you to use tone-access repeaters. The pocket beep alerts you when a matching tone frequency is received. The tone scan detects the subaudible tone that is used for repeater access.

Powerful 5.5W of output power

The IC-V80/E offers a just-right mix of power and size. 5.5 watts of high power will work to get your message through. Get up to 19 hours* of operating time with the Li-ion battery pack (BP-265) or 13 hours with the Ni-MH (BP-264). All that power comes in an easy to hold and use size – not too big, not too small.

* Typical operation. 5:5:90 duty cycle with power save on.

Internal VOX function

The IC-V80/E has internal VOX (Voice Operated Transmit) function for convenient hands-free operation with a compatible optional headset and plug adapter cable. Also, the VOX gain and VOX delay time are adjustable.

IP54 and MIL-STD-810 rugged construction

The dust protection and water-resistance equivalent to IP54 provides reliable operation for practical outdoor operation. The IC-V80/E tested to and passed 11 categories of MIL-STD-810 environmental tests.

Other features

- WX channel and weather alert function (USA version only)
- Program, memory, skip, priority and tone scans
- Power save function
- BNC type antenna connector
- Automatic repeater function (USA version only)
- 1750Hz tone for European repeater access (IC-V80E only)
- TOT (time out timer) setting
- Repeater lockout and busy channel lockout
- PC programmable with optional CS-V80
- Transceiver-to-transceiver cloning (Optional)
- Direct keypad frequency entry
- DTMF autodial memories
- Auto power off
- LCD backlight
- Wide/narrow channel spacing

A total of 207 memory channels

The IC-V80/E has a total of 207 memory channels, including 200 regular channels, 6 scan edges and 1 call channel. The channel name is programmable with 5 characters for easy recognition.



Dust Protection



Water Resistance



Transit Drop Test
(Photo shows image)



SPECIFICATIONS

GENERAL	
Frequency coverage IC-V80 (USA, Australia) IC-V80E (Europe, UK)	TX: 144–148MHz, RX: 136–174MHz* TX/RX: 144–146MHz * Guaranteed range 144–148MHz
Type of emissions	F2D, F3E (FM)
Number of channels	207 channels (include 6 scan edges and 1 call)
Antenna impedance	50Ω (BNC)
Power supply requirement	7.2V DC
Operating temperature range	–20°C to +60°C; –4°F to +140°F (Radio only)
Frequency stability	±2.5ppm (–20°C to +60°C) at 25°C
Current drain (approx.) Tx High (5.5W) Rx Max. audio Internal SP External SP Stand-by/Power save	1.4A typ. 310mA typ. (16Ω load) 180mA typ. (8Ω load) 65mA/20mA typ.
Dimensions (W×H×D) (Projections not included)	58 × 112 × 30 mm; 2.28 × 4.41 × 1.18 in
Weight (approx.)	140g; 4.9oz (without battery pack) 360g; 12.7oz (with BP-264 and FA-B2E)

TRANSMITTER	
Output power (at 7.2V)	5.5/2.5/0.5W (High/mid/low)
Max. frequency deviation	±5.0kHz/±2.5kHz (Wide/narrow)
Spurious emissions	Less than –60dB
Ext. microphone connector	3-conductor 2.5(d)mm (1/10")/2.2kΩ

RECEIVER	
Sensitivity	0.14μV typ. (at 12dB SINAD)
Squelch sensitivity	0.1μV typ. (threshold)
Selectivity	70dB/50dB typ. (Wide/narrow)
Intermodulation	70dB/65dB typ. (Wide/narrow)
Spurious and image rejection	75dB typ.
Audio output power Internal SP External SP	750mW typ. (16Ω load) 450mW typ. (8Ω load)
External speaker connector	3-conductor 3.5(d) mm (1/8")/8Ω

All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain Blowing/Drip	506.4	I, III
Humidity	507.4	–
Salt Fog	509.4	–
Dust Blowing	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard	
Dust & Water	IP54 (Dust-protection and water resistant)

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries. All other trademarks are the properties of their respective holders.

Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc.

12421 Willows Road NE,
Kirkland, WA 98034, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17A,
Delta, B.C., V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom Brazil

Rua Ibororé, 444 Padre Eustáquio
Belo Horizonte MG,
CEP: 30130-150, Brazil
Phone: +55 (31) 3582 8847
Fax: +55 (31) 3582 8987
E-mail: sales@icombrasil.com

Icom (Europe) GmbH

Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone: +49 (6196) 76685-0
Fax: +49 (6196) 76685-50
E-mail: info@icom-europe.com
URL: <http://www.icom-europe.com>

Icom Spain S.L.

Ctra. Rubí, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom Polska Sp. z o.o.

80-286 Gdansk, Jaskowa Dolina St. 75, Poland
Phone: +48 (58) 551 0484
Fax: +48 (58) 551 4720
E-mail: icompolska@icompolska.com.pl
URL: <http://www.icompolska.com.pl>

Icom (UK) Ltd.

Blacksole House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone: +44 (0) 1227 741741
Fax: +44 (0) 1227 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejonc des Moulains, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



Battery packs	Type and capacity	Operating time* (Approx.)
BP-263	AA (LR6) batteries x 6	–
BP-264	Ni-MH, 7.2V 1400mAh	13 hours
BP-265	Li-Ion, 7.4V 1900mAh (min.) 2000mAh (typ.)	19 hours

* Tx: Rx: standby = 5:5:90. Power save function ON.

REGULAR CHARGER
For BP-264 (Ni-MH battery)



BC-147S/BC-206S*1 BC-192
Charges the BP-264 in 16 hours (approx.).

RAPID CHARGER
For BP-264 (Ni-MH battery)



BC-123S*2 BC-191
Charges the BP-264 in 2 hours (approx.).

RAPID CHARGER
For BP-265 (Li-Ion battery)



BC-123S*2 BC-193
Charges the BP-265 in 2.5 hours (approx.).

*1 BC-147SA for 120V AC. SV for 240V AC. BC-206SE for 230V AC. *2 BC-123SA for 120V AC. SE for 230V AC. SV for 240V AC.

MULTI-CHARGER
For BP-264/BP-265



BC-197

CIGARETTE LIGHTER CABLE & POWER SUPPLY CABLES



CP-23L For use with BC-191 or BC-193
OPC-515L For use with BC-191, BC-192 or BC-193
OPC-656 For use with BC-197

HEADSETS and PLUG ADAPTER CABLE



HS-94 Earhook type
HS-95 Behind-the-head type
HS-97 Throat type
OPC-2004 Required when using any of these headsets

SPEAKER-MICROPHONES



HM-158LA
HM-159LA

EARPHONE MICROPHONE



HM-153LA

CHARGER BRACKET



MB-130 For use with BC-191, BC-192 or BC-193

CS-V80 CLONING SOFTWARE
+ **OPC-478/UC CLONING CABLE**
OPC-478UC is a USB cable type.
OPC-474 CLONING CABLE
Transceiver-to-transceiver cloning cable.
FA-B2E VHF ANTENNA
Same as supplied.
MB-124 BELT CLIP
Alligator type clip. Same as supplied.
CHARGER ADAPTERS
• **AD-120** for BP-264 • **AD-121** for BP-265
Either AD-120 or AD-121 charger adapters are supplied with the BC-197, depending on BC-197's version.



The "3D GENUINE Icom label" is attached to the rear chassis under the battery. Check the Icom website for details: <http://www.icom.co.jp/world/genuine-info/>

Your local distributor/dealer: